
Comm. Adapters, Signal Conv.

**BOS S-F01** 

Order Code: BAE002H







| _  |      |        |     |          |     |    |    |   |  |
|----|------|--------|-----|----------|-----|----|----|---|--|
| Ba | CI   | $\sim$ | TΩ  | 2        | rı. | IΝ | .Ο | c |  |
| பவ | . 31 | L.     | 110 | $\alpha$ | L.L | 41 | ~  | - |  |

Approval/Conformity CE WEEE Function Switching amplifier up to 400 mA Output converter (PNP/NPN) Switching inverter (NO/NC)

for S4, switching output on pin 4

400 mA

2.4 Vpp

**Electrical connection** 

Connection M12x1

Connection slots M12x1-Female, 4-pin

**Electrical data** 

Current consumption without load, 10 mA

max.

Use

Input frequency max. 10000 Hz Input resistance ≥ 10 kOhm Operating voltage Ub 10...30 VDC **Protection class** Rated insulation voltage Ui 75 V DC

Rated operating current le

Residual ripple max.

## **Environmental conditions**

Ambient temperature 0...60 °C Protection degree IP67

**Functional safety** 

MTTF (40 °C) 923 a

Material

Housing material PRT PA

Mechanical data

Dimension Ø 20 x 60 mm Mounting Union nut M12x1

Output/Interface

Digital inputs PNP

**Duration of time function** 1...65535 ms Switching output NPN normally open/normally

closed (NO/NC)

## Remarks

For additional information, refer to user's guide.

For more information about MTTF and B10d see MTTF / B10d Certificate

Indication of the MTTF- / B10d value does not represent a binding composition and/or life expectancy assurance; these are simply experiential values with no warranty implications. These declared values also do not extend the expiration period for defect claims or affect it in any way.

**BOS S-F01** 

Order Code: BAE002H




## **Connector Drawings**





## **Wiring Diagrams**



Subject to change without notice: 122423