

PRODUCT  
**VLT® AUTOMATIONDRIVE FC 300**

STATUS  
**COMPLETE**

RESET CONFIGURATION CANCEL

Configure by Nomenclature Code or Material Number

CONFIGURE

CONFIGURATION HAS CHANGED.



<b>Product Group</b>	(FC-) VLT® AutomationDrive FC-	Display all Options
<b>Series</b>	(302) 302	Display all Options
<b>Power Rating</b>	(P22K) 22 KW / 30 HP	Display all Options
<b>Phase</b>	(T) Three phase	Display all Options
<b>Mains Voltage</b>	(5) 380 - 500 VAC	Display all Options
<b>Enclosure</b>	(E20) IP20 / Chassis	Display all Options
<b>RFI Filter</b>	(H1) RFI Class A1/B (C1)	Display all Options
<b>Brake - Safe Stop</b>	(X) No brake chopper	Display all Options
<b>LCP</b>	(G) Graphical Loc. Cont. Panel	Display all Options
<b>Coating PCB</b>	(X) Not coated PCB	Display all Options
<b>Mains Option</b>	(X) No Mains Option	Display all Options
<b>Adaptation A</b>	(X) Standard Cable Entries	Display all Options
<b>Adaptation B</b>	(X) No adaptation	Display all Options
<b>Software Release</b>	(SXXX) Latest release std. SW.	Display all Options
<b>Software Language Pack</b>	(X) Standard Language Pack	Display all Options
<b>A Option</b>	(AX) No A Option	Display all Options
<b>B Option</b>	(BX) No B Option	Display all Options
<b>C0 Option MCO</b>	(CX) No C0 option	Display all Options
<b>C1 Option</b>	(X) No C1 option	Display all Options
<b>C Option Software</b>	(XX) No software option	Display all Options
<b>D Option</b>	(DX) No D option	Display all Options
<b>Frame Size</b>	(B4) B4	Display all Options
<b>Typecode Part 1</b>	FC-302P22KT5E20H1XGX	
<b>Typecode Part 2</b>	XXXSXXXAXBXCXXXDX	
<b>Product Catalog</b>	(GLBL) Global (Standard)	Display all Options
<b>Power 160% (HO) [KW]</b>	22	
<b>Power 110% (NO) [KW]</b>	30	
<b>Height [mm]</b>	530	

PRODUCT  
**VLT® AUTOMATIONDRIVE FC 300**

MODELCODE

**FC-302P22KT5E20H1XGXXXXSXXXAXBXCXXXDX**

<b>Width w/ no C options [mm]</b>	230,0
<b>Depth [mm]</b>	242,0
<b>Depth with Option A/B [mm]</b>	242,0
<b>kVA</b>	30,5
<b>Power Loss NO [W]</b>	739
<b>Power Loss NO [W]</b>	739
<b>Power Loss HO [W]</b>	547
<b>Power Loss HO [W]</b>	547
<b>Continuous Current (NO) [A]</b>	61
<b>Intermittent Current (NO) [A]</b>	67,1
<b>Continuous Current (NO) [A]</b>	52
<b>Intermittent Current (NO) [A]</b>	57,2
<b>Continuous Current (HO) [A]</b>	44
<b>Intermittent Current (HO) [A]</b>	70,4
<b>Continuous Current (HO) [A]</b>	40
<b>Intermittent Current (HO) [A]</b>	64
<b>Calculated Gross Weight</b>	20,800
<b>Calculated Net Weight [kg]</b>	20,500
<b>Vendor</b>	(ERR01) Cannot Determine Vendor
<b>Modelcode01</b>	FC-302P22KT5E20H1XGX
<b>Modelcode02</b>	XXSXXXXXBXCXXXXDX

[Display all Options](#)

 [ACCEPT](#)