



## 175G0096 🗷

## **VLT® Control Panel LCP 501**

The VLT® LCP 501 ensures seamless plug and play communication and control of VLT® Soft Starter MCD 500. With the Control Panel VLT® LCP 501 being a full function interface, everything you can do on the VLT® Soft Starter MCD 500 is possible via the LCP 501.

Language selection: English, Chinese, German, Spanish, Portuguese, French, Italian, Russian.

The VLT® LCP 501 is connected to the MCD 500 by using a 3m cable using 9 pin (D-sub) plug.

- o Same user interface as VLT® Soft Starter MCD500
- o Plug & play with MCD500
- o Copy/ paste of parameters
- o Multiple monitoring setup
- o Door-mount kit 3m cable
- o IP65 (NEMA 12)

## PRODUCT DETAILS

| Gross weight            |        | 0.47 kg        |
|-------------------------|--------|----------------|
| Net weight              |        | 0.347 kg       |
| Volume                  |        | 1.201          |
| EAN                     |        | 5710107607778  |
| POWER OPTIONS MCD 500 S | SERIES |                |
| MCD Series              | 5      | (5) 500 Series |

For Documents, Software, Visuals and more information, please use this link to visit the product page on Danfoss Product Store 🖸

Danfoss can accept no responsibility for possible errors in catalogs, brochures and other printed material. Danfoss reserves the right to alter its products without notice. This also applies to products already on order provided that such alterations can be made without sub-sequential changes being necessary in specifications already agreed. All trademarks in this material are property of the respective companies. Danfoss and the Danfoss logotype are trademarks of Danfoss A/S. All rights reserved.